# SICOM3009BA



## 9 Port Layer 2 Managed Switch

- 3 1000Base-x ports with SFP connecters,6 10/100Base-T(x) ports with RJ45 connecters.
- Power dissipation less than 5.2w.
- Comply with IEC60079-11(GB3836.4) of explosive atmospheres.
- Dry contact for warning signal, support NO and NC.
- Support one key recovery
- With-out housing
- Embedded switch without housing





### Overview

SICOM3016BA serial is designed for use in explosive atmospheres environment, low consumption, without housing. Comply with intrinsic safety, have advanced insulation performance, damp proofing, support fiber transmitting and forwarding, multiple redundant topology, remote monitoring, etc. Apply to explosive atmospheres, high dust, corrosive condition, such as coal mine, chemical factory, oil field and so on.



### Software Functions

#### Redundancy

Support DT-Ring, DT-Ring+, recover time with in 50ms when a link failed. Support STP/RSTP that meet 802.1d and 802.1w

#### Multicast

Support IGMP Snooping and static multicast.

#### **Switching**

Support VLAN, PVLAN

Support ports trunking ,speed limit,broadcast storm suppression

#### **Service Quality**

Support SP,WRR queue scheduling

#### **Network Management**

Support CLI, Telnet, WEB manage. Mib, Kyvisionclient, SNMPv1/v2/v3, RMON Link Check,LLDP,SNTP,DHCP

#### **Network Security**

Support SSH,TACACS+

#### **Equipment Maintenance**

Support ports mirroring. Update APP by FTP

#### **Alarm Contact**

Support power warning Support port and ring block warning

# >>> Technical Specifications

#### **Technical Parameter**

#### Standard

- ▼ IEEE 802.3i,
- ▼ IEEE 802.3u,
- ▼ IEEE 802.3x.
- ▼ IEEE 802.1p,
- ▼ IEEE 802.1O.
- ▼ IEEE 802.1w

#### Protocol

- ▼ DT-Ring,DT-Ring+,DT-VLAN,RSTP;
- ▼ IGMP snooping;
- ▼ VLAN,PVLAN, ARP,QoS;
- ▼ Telnet,HTTP,HTTPS, FTP;
- ▼ SNMPv1/v2/v3,RMON,
- LLDP,SNTP,DHCPserver; ▼ SSH,TACACS+;

### **Switching**

Queue Priority 256 Number of VLANs VLAN ID 1~4093 Number of Multicast Groups 256 MAC Table Size 8K Packet Buffer Size 1Mbit Packet Forwarding Rate 5.4Mpps Forwarding Delay <10µs

#### **Interface**

Fast Ethernet Ports

- ▼ 10/100Base-T(X)auto negotation ,Connecter type is RJ45 Console Port
- ▼ Adopt RS232 protocol ,connecter type is RJ45 Alarming contactor
- Dry contact for warning signal, support NO and NC.
- ▼ 3 pin 5.08mm plugs, 0.5A at 125Vac,2Aat30Vdc

#### **LED**

LED on Front Panel

 Non-housing version support LED interface for user, Dimensions refer to hardware manual

#### **Button**

Reset:system reset

Default: system recover default configuration

#### **Power Requirements**

Input Voltage 33-5.5VDC

Power Connector

▼ 6pin 5.08mm spacing plug-in termianl block Power Consumption <3.9W.

2.06W in idle

Overload Protection Support Inverse Protection Support Redundancy Protection Support

### **Physical Characteristics**

Dimension 130mm×35mm×107mm(W×H×D)

Weights

Installation support location holes for users


#### **Environmental Limits**

-40°C -+75°C Operating Temperature -40°C -+85°C Storage Temperature 5-95%RH. Relative Humidity

#### Warranty

MTBF 376,919 hrs Warranty 5years

# Mechanical Drawing







# >> Ordering Information

	SICOM3009BA-EC-Ports-Connector-PS	
EC	Non-housing and Conformal Coating	
Ports		
3S6T	3 100Base-FX single-mode fiber ports; 6 10/100Base-T(X) fast Ethernet ports	
3M6T	3 100Base-FX multi-mode fiber ports; 6 10/100Base-T(X)fast Ethernet ports	
2S6T	2 100Base-FX single-mode fiber ports; 6 10/100Base-T(X)fast Ethernet ports	
2M6T	2 100Base-FX multi-mode fiber ports; 6 10/100Base-T(X)fast Ethernet ports	
Connector	100M fiber port specifications	
SC05	SC connector, multi-mode, 1310nm, 5km	
ST05	ST connector, multi-mode, 1310nm, 5km	
FC05	FC connector, multi-mode, 1310nm, 5km	
SC40	SC connector, single-mode, 1310nm, 40km	
ST40	ST connector, single-mode, 1310nm, 40km	
FC40	FC connector, single-mode, 1310nm, 40km	
SC60	SC connector, single-mode, 1310nm, 60km	
SC80	SC connector, single-mode, 1550nm, 80km	
PS		
L9-L9	3-5.5VDC, Redundant Power Inputs	

# Accessories

	Accessory	Model
--	-----------	-------

### Description

DT-FCZ-RJ45-01

Dustproof cover for RJ45 port